

# Delock 4 Port USB 3.0 Hub, 1 port USB power internal / external

## Description

This Delock USB 3.0 Hub expands your PC or laptop by four additional USB 3.0 ports as well as one USB port, which can be used as power supply for your USB devices. The Hub can be used either externally with the included power supply or internally in a 3.5" bay of your PC. Just connect the power cable of your PC power supply to the Hub and lead the USB 3.0 cable outside. You will also find three different panels in black, silver and beige included in delivery, in order to change the colour of the front part.



**Item no. 61898**

EAN: 4043619618989

Country of origin: China

Package: Retail Box

## Technical details

- Connectors:
  - front side:
    - 1 x USB Type-A charging port max. 2 A
    - 4 x USB 3.0 Type-A female
  - back side:
    - 1 x USB 3.0 Type-B downstream port
    - 1 x DC 5 V power connector
    - 1 x 4 pin power connector
    - 1 x On / Off switch (only for external use)
- Data transfer rate up to:
  - SuperSpeed 5 Gbps,
  - Hi-Speed 480 Mbps,
  - Full-Speed 12 Mbps,
  - Low-Speed 1.5 Mbps
- For external connection or installation into a 3.5" bay
- Use as self-powered (with power supply) or bus-powered (without power supply)
- LED indicator for power and access
- Dimensions (LxWxH): ca. 101,4 x 70,0 x 25,9 mm
- Hot Plug, Plug & Play

---

## Power supply specification

- Input: AC 100 ~ 240 V / 50 ~ 60 Hz / 0.5 A
- Output: 5 V / 3 A
- Ground outside, plus inside
- Dimensions:
  - inside:  $\varnothing$  ca. 1.35 mm
  - outside:  $\varnothing$  ca. 3.5 mm
  - length: ca. 10.5 mm

---

## System requirements

- Linux Kernel 2.6 or above
- Mac OS 10.5 or above
- Windows Vista/Vista-64/7/7-64/8.1/8.1-64/10/10-64
- External use: PC or laptop with a free USB port
- Internal use: PC with one free 3.5" bay, one 4 pin power cable and one free USB Type-A port

---

## Package content

- Hub USB 3.0
- USB 3.0 cable
- Panel black, silver, beige
- External power supply 5 V / 3 A
- User manual

---

## Images

